

Note: The below changes (in red) to the TASMA Band Plan, will designate Digital Voice simplex frequencies.

BAND PLAN

- 144.000 - 144.100 CW only (Part 97.61a)
- 144.100 - 144.275 AM, SSB & other weak signal/narrow bandwidth modes
- 144.275 - 144.300 CW Propagation Beacons
- 144.310 - 144.375 FM simplex (unchannelized)
- 144.390 - Digital (packet) -- (APRS)
- 144.405 - 144.490 FM simplex (unchannelized)
- 144.505 - Repeater output (paired with 145.105 input)
- 144.520 - 144.880 Repeater inputs: 20 kHz spacing
- 144.895 - Repeater output (paired with 145.495 input)
- 144.910 - Cross-band repeater input/output (not coordinated, CTCSS use mandatory)
- 144.930 - Portable repeater output, shared (paired with 147.585 input)
- 144.950 - Repeater output (paired with 147.405 input)
- 144.970 - Digital (packet)
- 144.985 - 145.015 Digital voice repeater inputs (i.e. D-Star): 10 kHz spacing
- 145.030 - 145.090 Digital (packet): 20 kHz spacing
- 145.105 - Repeater input (paired with 144.505 output)
- 145.120 - 145.480 Repeater outputs: 20 kHz spacing
- 145.495 - Repeater input (paired with 144.895 output)
- 145.510 - 145.660 FM simplex: 15 kHz spacing, **DV frequencies – 145.510, 145.525, 145.660**
- 145.675 - 145.785 Fixed simplex auxiliary stations (internet links, remote base, etc.: 15 kHz spacing),
DV frequencies – 145.675, 145.570, 145.785
- 145.800 - 146.000 OSCAR satellite use
- 146.010 - 146.385 Repeater input/output (15 kHz inverted tertiary sub-band plan; see text)
- 146.400 - Repeater input (paired with 147.435 output)
- 146.415 - Repeater input (paired with 147.450 output)
- 146.430 - ATV FM simplex
- 146.460 - Fixed simplex auxiliary station (internet links, remote base, etc.)
- 146.475 - Repeater input (paired with 147.420 output)
- 146.490 - Repeater input (paired with 147.495 output)
- 146.505 - Repeater input (paired with 147.465 output)
- 146.520 - National FM simplex
- 146.535 - 146.595 FM simplex: 15 kHz spacing
- 146.610 - 147.390 Repeater input/output (15 kHz inverted tertiary sub-band plan; see text)
- 147.405 - Repeater input (paired with 144.950 output)
- 147.420 - Repeater output (paired with 146.475 input)
- 147.435 - Repeater output (paired with 146.400 input)
- 147.450 - Repeater output (paired with 146.415 input)
- 147.465 - Repeater output (paired with 146.505 input)
- 147.480 - FM simplex
- 147.495 - Repeater output (paired with 146.490 input)
- 147.510 - FM simplex
- 147.525 - Cross-band repeater input/output (not coordinated, CTCSS use mandatory)
DV frequency – 147.525 (secondary usage)
- 147.540 - 147.570 Digital voice repeater outputs (i.e. D-Star): 10 kHz spacing
- 147.585 - Portable repeater input, shared (paired with 144.930 output)
- 147.600 - 147.990 Repeater input/output (15 kHz inverted tertiary sub-band plan; see text)